

Linux From Scratch - Version 12.1-systemd		
Chapter 9. System Configuration		
	/	

9.4.

9.4.1.

9.3 " " USB TV 가 /dev /dev/video0 , /dev/video1 가 , 가 udev 9.2 " " BLFS 가 가 (Linux 가) /sys/class /sys/block /sys/class/video4linux/videoX (ID /).


```
udevadm info -a -p /sys/class/video4linux/video0
```

```
cat > /etc/udev/rules.d/83-duplicate_devs.rules << "EOF"

# Persistent symlinks for webcam and tuner
KERNEL=="video*", ATTRS{idProduct}=="1910", ATTRS{idVendor}=="0d81",
SYMLINK+="webcam"
KERNEL=="video*", ATTRS{device}=="0x036f", ATTRS{vendor}=="0x109e",
SYMLINK+="tvtuner"

EOF
```

/dev/video0 /dev/video1 (/dev/tvtuner /dev/webcam .), 가



From:
<https://www.gamu.kr/dokuwiki/> -

Permanent link:
https://www.gamu.kr/dokuwiki/linuxfromscratch/12.1/157-managing_devices



Last update: **2024/06/15 13:03**